



HUSQVARNA G1300P

Small, compact, durable generator with 0.8kW (50Hz) output for efficient powering of homes and work sites. 6L fuel tank for tough, reliable performance from its easy-start petrol engine in all conditions. Ergonomic design allows easy portability, while a user-friendly dashboard means easy usability, even in emergencies.



External fuel cap for easy refueling

External fuel cap for easy refueling



Visible fuel level

Transparent fuel indicator makes it easy to check fuel level.

FEATURES

- Visible fuel level
- External fuel cap for easy refueling

Technical Specifications		
CAPACITY		
Horsepower		1.1 hp
Power		800 W
DIMENSIONS		
Article gross weight		29200 g
Article net weight		28000 g
Weight		28 kg
EMISSION DATA		
Exhaust emissions (CO2 EU V)		603 g/kWh
ENGINE		
Cylinder displacement		98.5 cm ³
Motor/engine manufacturer		Weima
EQUIPMENT		
Air filter type		Dry
Starter		Recoil
Technical Platform		Generators EMM
LUBRICANTS		
Engine oil capacity (L)		0.45
Engine oil type		SAE 10W-30
Fuel consumption		395 g/kWh
Fuel tank volume (with reserve)		6 l
MATERIALS		
Master pack: Paper + Cardboard		0 g
Metal total		0 g
Paper + Cardboard total		0 g
PE total		0 g
PET total		0 g
Plastic foil		0 g
Plastic rigid		0 g
Plastic total		0 g
PS/EPS/HIPS total		0 g
PACKAGING		
Packaging height		415 mm
Packaging length		485 mm
Packaging volume		75.48 dm ³
Packaging width		375 mm
Quantity in Master pack		1